
NOTES: (UNLESS OTHERWISE SPECIFIED)


1. DIMENSIONS ARE IN INCHES [CENTIMETERS]
2. DIMENSIONS ARE FOR REFERENCE ONLY.
3. PRODUCT I/D SERIAL NO. DECAL

REV	ECO	DESCRIPTION	DATE	BY
A2	MX4107	UPDATE TO NEW DESIGN, FIX CONNECTION TABLES	5/10/2010	BLF
A2	----	SHOW THE CORRECT LOCATION OF THE SERIAL LABEL	01/23/2012	HGC




REAR VIEW


(ROTATED)
(TIEDOWN BAR REMOVED FOR CLARITY)



TOP VIEW




FRONT VIEW



REFERENCE SCHEMATIC

TYP 28 CIRCUITS FOR 097-0128-0008 ONLY

PART NUMBER	DESCRIPTION	CONNECTOR
097-0128-0006	DS1:PNL,INTFC,28,RJ48X,19X1.75	RJ48X
097-0128-0007	DS1:PNL,INTFC,28,RJ48C,19X1.75	RJ48C
097-0128-0008	DS1:PNL,INTFC,28,RJ48C,TRNS/RCV INTERNALLY CROSS-CONNECTED,19"x1.75",WHITE	RJ48C



REFERENCE SCHEMATIC

TYP 28 CIRCUITS FOR 097-0128-0006/7 ONLY

DESIGNED BY: B. EGBERT	DATE: 1/24/2003
DRAWN BY: B. EGBERT	DATE: 1/24/2003

NOT FOR REPRODUCTION COPYRIGHT: 2003

This document contains proprietary information that is property of TELECT, INC., Spokane, Washington. It is intended for the exclusive use of our customer for information, installation, and/or service. The recipient agrees not to reproduce or copy this document or its contents in whole or in part without prior written permission from TELECT, INC. This document must be returned promptly if no longer needed or upon written request from TELECT, INC.

Telect®
CONNECTING THE FUTURE
23321 East Knox Avenue
Liberty Lake, Washington 99019
(509) 926-6000

TITLE: CUSTOMER DRAWING

DS1,CIP,CHASSIS,1.75X19

DRAWING NO	SHEET SIZE	UNITS
097-0128-000X	B	IN

PROJECT	SCALE	SHEET	REV
C045	.35:1	1 OF 2	A2

REV	ECO	DESCRIPTION	DATE	BY
A2	MX4107	SEE SHEET 1	5/10/2010	BLF

097-0128-0006/0007 CONNECTION TABLE 1

TRANSMIT (XMT)						RECEIVE (RX)					
CIRCUIT NO.		RJ48-PIN#	J1	REAR XMT WW PIN #		CIRCUIT NO.		RJ48 - PIN #	J2	REAR RCV WW PIN #	
1	T	5	33	1 - TIP		1	T	2	33	1 - TIP	
	R	4	1	1 - RING			R	1	1	1 - RING	
REPEATED						REPEATED					
28	T	5	60	28 - TIP		28	T	2	60	28 - TIP	
	R	4	28	28 - RING			R	1	28	28 - RING	

097-0128-0008 CONNECTION TABLE 2 (X-CONN)

TRANSMIT (XMT)						RECEIVE (RX)					
CIRCUIT NO.		RJ48 - PIN #	J1	REAR XMT WW PIN #		CIRCUIT NO.		RJ48 - PIN #	J2	REAR RCV WW PIN #	
1	T	2	33	1 - TIP		1	T	5	33	1 - TIP	
	R	1	1	1 - RING			R	4	1	1 - RING	
REPEATED						REPEATED					
28	T	2	60	28 - TIP		28	T	5	60	28 - TIP	
	R	1	28	28 - RING			R	4	28	28 - RING	

DRAWING NO			SHEET SIZE	UNITS
097-0128-000X			B	IN
	PROJECT	SCALE	SHEET	REV
	C045	NONE	2 OF 2	A2